

5300 Beethoven Street, Los Angeles, CA 90066 TEL: (310)306-5556 • FAX: (310)577-9779

WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 4018

2.5 - 2.7 GHz 30 WATTS LINEAR POWER RF AMPLIFIER

Solid State Band-specific High Power RF Amplifier

The 4018 is a 30 Watt band-specific amplifier that covers the 2.5-2.7 GHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all Ophir_{RF} amplifiers, the 4018 comes with an extended multiyear warranty.

CIRCUIT PROTECTIONS

- ♦ Infinite Load VSWR
- ♦ RF Input Overdrive
- ♦ Thermal Overload
- ♦ Over Current
- ♦ Over Voltage

AVAILABLE OPTIONS

- ♦ LCD Digital Display
- ♦ IEEE-488 GPIB
- ♦ Gain Adjustment
- ♦ Automatic Level Control
- ♦ Extended Temperature Range
- ♦ Rear Panel Connectors
- ♦ Rack Mounting Slide
- ♦ Different Case Styles

	Parameter	Specification
<u>Electrical</u>	<u> </u>	<u> </u>
1	Frequency Range	2.5 – 2.7 GHz
2	Saturated Output Power	30 Watts typical
3	Power Output @ 1dB Comp.	25 Watts min
4	Small Signal Gain	+44 dB min
5	Small Signal Gain Flatness	<u>+</u> 1.0 dB max
6	IP ₃	+55 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 1 dB comp.
9	Spurious Signals	> -60 dBc
10	Input/Output Impedance	50 Ohms nominal
11	AC Input Power	120 Watts max
12	AC Input	100 – 240 VAC, single phase
13	RF Input Overdrive	+10 dB over 1 dB Compression
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	A/AB Linear
<u>Mechanical</u>		
16	Dimensions	19" x 3.5" x 18"
17	Weight	25 lb. max
18	Connectors	Type-N
19	Grounding	Chassis
20	Cooling	Internal Forced Air
<u>Environmental</u>		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

