



5300 Beethoven Street, Los Angeles, CA 90066
 TEL: (310)306-5556 • FAX: (310)577-9887
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 4039R

292 - 320 MHz
 250 WATTS
 LINEAR POWER RF AMPLIFIER

Solid State Power RF fier

High Ampli- fier

The 4039R is a 250 Watt RF amplifier that covers the 292 – 320 MHz frequency range. This small and light-weight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 4039R comes with an extended multi-year warranty.

	Parameter	Specification @ 25° C
Electrical		
1	Frequency Range	292 – 320 MHz
2	Saturated Output Power	250 Watts typical
3	Power Output @ 1dB Comp.	200 Watts min
4	Gain (Keyed) *	+53 dB min
5	Gain (Un-Keyed) *	0 dB max
6	TX KEY line *	Ground = Keyed
7	TX Rise (Turn-on) Time	< 100 us
8	TX Fall (Turn-off) Time	< 100 us
9	Noise Figure	< 10 dB typical
10	Input VSWR	2:1 max
11	Harmonics	-20 dBc typical @ 200 Watts
12	Spurious Signals **	> -60 dBc typical @ 200 Watts
13	Input/Output Impedance	50 Ohms nominal
14	AC Input	100 – 240 VAC, single phase
15	RF Input	0 dBm
16	Class of Operation	AB
Mechanical		
17	Dimensions	19" x 5.25" x 20"
18	Weight	40 lb. max
19	Connectors	Type-N
20	Grounding	Chassis
21	Cooling	Internal Forced Air
Environmental		
22	Operating Temperature	0° C to +50° C
23	Operating Humidity	95% Non-condensing
24	Operating Altitude	Up to 10,000' Above Sea Level
25	Shock and Vibration	Normal Truck Transport

CIRCUIT PROTECTIONS

- ◇ Thermal Overload
- ◇ Over Current
- ◇ Over Voltage

INCLUDED FEATURES

- ◇ Transmit key indicator LED
- ◇ 20 dB Variable Gain Control (Front)

* Spurious Test Procedure

- Turn GAIN Control on Front Panel Fully CW (Max Gain setting).
- Set RF Input Power to 0dBm at 300 MHz.
- “KEY” amplifier and Observe the RF Output on a Spectrum Analyzer.
- While adjusting the GAIN Control through its full range, examine the RF Output Spectrum from 30kHz through 1GHz per Specification.

** Delta KEY and Un-KEY Shutdown Test Procedure

- Turn GAIN Control on Front Panel Fully CW (Max Gain setting).
- Set RF Input Power to 0dBm at 300 MHz.
- “KEY” amplifier and measure ≥ 53 dBm RF Output Power.
- “Un-KEY” amplifier and measure < 0 dBm RF Output Power.