



5300 Beethoven Street, Los Angeles, CA 90066
TEL: (310)306-5556 • FAX: (310)577-9779
WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 4010
800 - 1000 MHz
300 WATTS
LINEAR POWER RF AMPLIFIER

Solid State
Band-specific High
Power RF Amplifier

The 4010 is a 300 Watt band-specific amplifier that covers the 800 – 1000 MHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all Ophir_{RF} amplifiers, the 4010 comes with an extended multiyear warranty.

CIRCUIT PROTECTIONS

- ◇ Infinite Load VSWR
- ◇ RF Input Overdrive
- ◇ Thermal Overload
- ◇ Over Current
- ◇ Over Voltage

AVAILABLE OPTIONS

- ◇ LCD Digital Display
- ◇ IEEE-488 GPIB
- ◇ Gain Adjustment
- ◇ Automatic Level Control
- ◇ Extended Temperature Range
- ◇ Rear Panel Connectors
- ◇ Rack Mounting Slide
- ◇ Different Case Styles

	<u>Parameter</u>	<u>Specification</u>
<u>Electrical</u>		
1	Frequency Range	800 – 1000 MHz
2	Saturated Output Power	300 Watts typical
3	Power Output @ 1dB Comp.	150 Watts min
4	Small Signal Gain	+56 dB min
5	Small Signal Gain Flatness	± 1.5 dB max
6	IP ₃	+61 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 1 dB comp.
9	Spurious Signals	> -60 dBc
10	Input/Output Impedance	50 Ohms nominal
11	AC Input Power	1600 Watts max
12	AC Input	100 – 240 VAC, single phase
13	RF Input Overdrive	+10 dB over 1 dB Compression
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	A/AB Linear
<u>Mechanical</u>		
16	Dimensions	19" x 8.75" x 20"
17	Weight	80 lb. max
18	Connectors	Type-N
19	Grounding	Chassis
20	Cooling	Internal Forced Air
<u>Environmental</u>		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

