

Combination Wave Generator

PG 10 - 504

Surge voltage
1.2/50 μ s
0.2-10 kV

Surge current
8/20 μ s
0.1-5 kA

acc. to IEC 61000-4-5,
IEEE 587



The Combination Wave Generator PG 10-504 is a combined impulse-current-/impulse-voltage generator which, for high-impedance loads, $R_L > 100\Omega$, delivers a standard impulse voltage with waveform 1.2/50 μ s and, for short-circuited output, a standard impulse current with waveform 8/20 μ s.

The generator allows surge testing of components and devices, galvanic coupling of surges to cable shields, shielded enclosures and cabinets as well as testing electromagnetic compatibility, EMC, of electronic devices and systems against pulsed and conducted interference.

Using an external Coupling-/Decoupling Network allows superimposition of the combination wave generator's output to the mains voltage of the device under test. The test set-up is suitable for surge immunity testing of electronic systems and devices full compliant to IEC 61000-4-5 and IEEE 587. Demonstrating such immunity is generally a requirement for compliance with the requirements of the European EMC directive, a necessary step leading to the final attachment of the CE mark.

Executing surge immunity tests at power supply a line triggering of high-voltage pulses is accomplished synchronous with mains. The precise trigger point can be shifted between 0 to 360 ° after the zero crossing of the mains voltage. The polarity of the output voltage is selectable. Positive, negative or alternating polarity of the output voltage can be pre selected.

The PG 10-504 excels by its compact design, simple handling and precise reproducibility of test impulses. The output current- and voltage waveforms, due to built-in sensors, can be recorded via separate signal outputs for current and voltage.

PG 10-504 features a microprocessor controlled user interface and a 5" touch screen unit for ease of use. The microprocessor allows the user to execute either standard test routines or a "user defined" test sequence. The test parameters and even the settings of an external CDN, which are shown on the built in display, are easily adjusted by means of touch screen. A standard USB port provides the ability to print a summary of the test parameters to a USB stick.

Moreover, all generator functions may be computer controlled.

The software program PG-REMOTE allows full remote control of the test generator via fiber optic Ethernet interface as well as documentation and evaluation of test results, accordingly to the IEC 17025. To record definite impulses, it is equipped with an Impulse Recording Function (IRF)

TECHNICAL SPECIFICATIONS	PG 10-504
Mainframe:	
Microprocessor controlled touch panel	5", 800X480, 24 bit
Optical Ethernet Interface for remote control of the generator	optional
Interface for saving reports	USB
Optical-interface for remote control of external CDN's	Built-in
External Trigger input / output	10 V an 1 kΩ
Connector for external safety interlock loop and external red and green warning lamps acc. to VDE 0104	24 V = 230 V, 60W
Mains power	230 V , 50/60 Hz
Dimensions: desk top case W * H * D	453*320*520 mm ³
Weight	30 kg
Combination Wave Generator acc. to IEC 61000-4-5: 2014	
Test voltage, (open circuit condition)	0.2 - 10 kV ± 10 %
Waveform acc. to IEC 60	1.2 / 50 μs ± 30/20 %
charging time for max. charging voltage	0.1 - 5.0 kA ± 10 %
Waveform acc. to IEC 60	8 / 20 μs ± 20 %
Polarity of output voltage/current, selectable	pos/neg/alt
maximum stored energy	500 Joule
charging time for max. charging voltage	< 20s
HV-output: isolated from ground	HV-OUT, COM
Mains synchronous triggering :	
Phase shifting, digitally selectable	0 - 360 °, step 1°
Ext.Sync. Input for synchronisation to the external CDN mains	built-in
Optical output for control of external CDN	built-in
Display of peak values of pulse voltage and current	built-in
Monitor output for pulse output voltage	ratio = 1000 : 1 ± 5 %
Monitor output for pulse output current	10V ≙ 5 kA ± 5 %
Options:	
PG Remote software test package, running under Microsoft Windows, for the external control of the device includes 5 m long fibre optic cable and Ethernet PC Interface	
Generator prepared for power supply voltage at CDN input up to 3*690V≈	
Additional accessories available:	
Test cabinet	PA 503 / PA 505
Coupling/decoupling networks for immunity test	CDN 10416/32/64, CDN 2402/2410