

5300 Beethoven Street, Los Angeles, CA 90066 TEL: (310)306-5556 • FAX: (310)577-9887 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 4045

950 - 1450 MHz **60 WATTS** LINEAR POWER RF AMPLIFIER

Solid State Band-Specific High Power RF Amplifier

The 4045 is a 60 Watt band-specific amplifier that covers the 950 - 1450 MHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and comthis amplifier ponents, achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 4045 comes with an extended multiyear warranty.

	<u>Parameter</u>	Specification @ 25° C
<u>Electrical</u>		
1	Frequency Range	950 – 1450 MHz
2	Saturated Output Power	60 Watts typical
3	Power Output @ 1dB Comp.	40 Watts min
4	Small Signal Gain	+49 dB min
5	Small Signal Gain Flatness	<u>+</u> 1.0 dB max
6	IP ₃	+56 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 40 Watts
9	Spurious Signals	> -60 dBc typical @ 40 Watts
10	Input/Output Impedance	50 Ohms nominal
11	AC Input Power	400 Watts max
12	AC Input	100 – 240 VAC, single phase
13	RF Input	+10 dBm max
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	A/AB
<u>Mechanical</u>		
16	Dimensions	19" x 3.5" x 18"
17	Weight	30 lb. max
18	Connectors	Type-N
19	Grounding	Chassis
20	Cooling	Internal Forced Air
<u>Environmental</u>		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport Specifications subject to change without notice.

CIRCUIT PROTECTIONS

- ♦ Thermal Overload
- ♦ Over Current / Over Voltage

ORDERING MODELS

- Rear Panel Connectors
- ♦ F - Front Panel Connectors
- ♦ RE R model w/Control Option
- ♦ FE F model w/Control Option
- ♦ RT RE model w/Ethernet Interface
- ♦ FT FE model w/Ethernet Interface



RE Model Shown