



5300 Beethoven Street, Los Angeles, CA 90066
 TEL: (310)306-5556 • FAX: (310)577-9779
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

Solid State Broadband High Power RF Amplifier

The 5019 is a 100 Watt broadband amplifier that covers the 500 – 1000 MHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 5019 comes with an extended multiyear warranty.

CIRCUIT PROTECTIONS

- ◊ Infinite Load VSWR
- ◊ RF Input Overdrive
- ◊ Thermal Overload
- ◊ Over Current
- ◊ Over Voltage

AVAILABLE OPTIONS

- ◊ LCD Digital Display
- ◊ IEEE-488 GPIB
- ◊ Gain Adjustment
- ◊ Automatic Level Control
- ◊ Extended Temperature Range
- ◊ Rear Panel Connectors
- ◊ Rack Mounting Slide
- ◊ Different Case Styles

MODEL 5019

500 - 1000 MHz

100 WATTS

LINEAR POWER RF AMPLIFIER

	Parameter	Specification
Electrical		
1	Frequency Range	500 – 1000 MHz
2	Saturated Output Power	100 Watts typical
3	Power Output @ 1dB Comp.	60 Watts min
4	Small Signal Gain	+50 dB min
5	Small Signal Gain Flatness	± 1.5 dB max
6	IP ₃	+55 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 1 dB comp.
9	Spurious Signals	> -60 dBc
10	Input/Output Impedance	50 Ohms nominal
11	AC Input Power	600 Watts max
12	AC Input	100 – 240 VAC, single phase
13	RF Input Overdrive	+10 dB over 1 dB Compression
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	A/AB Linear
Mechanical		
16	Dimensions	19" x 5.25" x 20"
17	Weight	47 lb. max
18	Connectors	Type-N
19	Grounding	Chassis
20	Cooling	Internal Forced Air
Environmental		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

