

MODEL 5300683
0.8-4.2 GHz
15 WATTS
LINEAR POWER RF AMPLIFIER

**Solid State
 Broadband High
 Power RF Amplifier**

The 5300683 is a 15 Watt broadband amplifier that covers the 0.8-4.2 GHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 5300683 comes with an extended multiyear warranty.

	Parameter	Specification @ 25° C
Electrical		
1	Frequency Range	0.8-4.2 GHz
2	Saturated Output Power	15 Watts typical
	P1dB Output Power	11 watts min
4	Small Signal Gain	+12dB typical
5	Gain Flatness	± 2.0 dB max
6	IP ₃	+49 dBm typical
7	Input / Output VSWR	2:1 max
8	Harmonics	-20 dBc min @ 11 Watts
9	Spurious Signals	< -60 dBc max @ 11 Watts
10	Input/Output Impedance	50 Ohms nominal
11	DC Input Current	8.0 Amps max
12	DC Input	13 VDC nominal
13	RF Input	+32 dBm nominal for rated power
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	A/AB
Mechanical		
16	Dimensions	12.5 L x 5.1" W x 1.1" H
17	Weight	4 Lbs.
18	Connectors	SMA female
19	Grounding	Chassis
20	Cooling	Adequate Heatsink Required
Environmental		
21	Baseplate Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice.

Available Options

- ◇ Heat Sink
- ◇ Heat Sink and Fans
- ◇ Ophir RF Model 5303075 800-4200MHz, 1.5 Watt Driver Module

