



5300 Beethoven Street, Los Angeles, CA 90066
 TEL: (310)306-5556 • FAX: (310)577-9779
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5302029

1.8 - 2.0 GHz
80 WATTS
LINEAR POWER RF AMPLIFIER

**Solid State
 Band-specific High
 Power RF Amplifier**

The 5302029 is an 80 Watt band-specific amplifier that covers the 1.8 – 2.0 GHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 5302029 comes with an extended multiyear warranty.

	<u>Parameter</u>	<u>Specification</u>
<u>Electrical</u>		
1	Frequency Range	1.8 – 2.0 GHz
2	Instantaneous Bandwidth	60 MHz min
3	Saturated Output Power	80 Watts typical
4	Power Output @ 1dB Comp.	60 Watts min
5	Power Output CDMA	15 Watts typical
6	Small Signal Gain	+51 dB min
7	Gain Flatness	± 1.0 dB max
8	IP ₃	+58 dBm typical
9	Input VSWR	2:1 max
10	Harmonics	-20 dBc typical @ 1 dB comp.
11	Spurious Signals	> -60 dBc
12	Input/Output Impedance	50 Ohms nominal
13	DC Input Current @ 15W	15 Amps max
14	DC Input	13 – 15 VDC nominal
15	RF Input Overdrive	+10 dB over 1 dB Compression
16	RF Input Signal Format	CW/AM/FM/PM/Pulse
17	Class of Operation	A/AB Linear
<u>Mechanical</u>		
18	Dimensions	9" x 6.4" x 1.1"
19	Weight	3 lb. max
20	Connectors	SMA female
21	Grounding	Chassis
22	Cooling	Adequate Heatsink Required
<u>Environmental</u>		
23	Operating Temperature	0° C to +50° C
24	Operating Humidity	95% Non-condensing
25	Operating Altitude	Up to 10,000' Above Sea Level
26	Shock and Vibration	Normal Truck Transport

AVAILABLE OPTIONS

- ◇ Gain Adjustment
- ◇ Automatic Level Control
- ◇ Extended Temperature Range
- ◇ Thermal Overload
- ◇ Over Current
- ◇ Over Voltage
- ◇ Microprocessor Controlled
- ◇ Built-in Monitoring

